



Doc. No.78-1499-03

Workgroup CDDI/FDDI SBus Adapter Driver Version 4.1 for SunOS 4.1.x Release Note

Supplement to DOC-SBUSUG1 (Document Number 78-1277-01)

Introduction

This release note describes the features, modifications, and caveats of the Copper Distributed Data Interface (CDDI) and Fiber Distributed Data Interface (FDDI) SBus Adapter driver software Version 4.1 for SunOS Version 4.1.x. Refer to the *workgroup CDDI/FDDI SBus Adapter User Guide* for detailed information about the workgroup CDDI/FDDI SBus adapter.

Product Overview

The workgroup CDDI/FDDI SBus adapters are high-performance cards that connect a SPARCstation or SPARCserver to a CDDI or FDDI ring. The adapter provides a single attachment station (SAS) or dual attachment station (DAS) connection that is compliant with Station Management (SMT) 6.2 or 7.3. Refer to the chapter "Product Overview," of the *Workgroup CDDI/FDDI SBus Adapter User Guide* for a further explanation of product features and functions.

CDDI/FDDI SBus adapter models WA-C301TA, WA-C303TA, WA-C306TA, and WA-C308TA require CDDI/FDDI SBus adapter driver software Version 4.1 or higher for SunOS 4.1.x.

Version 4.1 Features

The following new features have been added to the CDDI/FDDI SBus adapter driver software Version 4.1:

- 1 Support for diskless boot workstations. For detailed information, refer to the *Workgroup CDDI/FDDI SBus Adapter User Guide*.
- 2 Support for the SunOS IP multicast kernel as per RFC 1054 using the SunOS Driver (multicast) Version 4.1 diskette.

Note The SunOS IP multicast driver only works with the SunOS Version 4.1.x multicast kernel.

Version 3.2 Features

The following new features have been added to the CDDI/FDDI SBus Adapter Driver software Version 3.2:

- 1 Support for SMT Revision 6.2 or 7.3 with turbo and SMT 6.2 for nonturbo SBus adapters. Table 1 is a matrix showing the correct flashcode file name to be downloaded depending on your SMT version and adapter card type.

Table 1 Flashcode File Matrix

File Name	SMT Version	Adapter Card Type	Product Number
sbus25.rom	6.2	Nonturbo	WA-C300, WA-C301M, WA-C303, WA-C305, WA-C306M, WA-C308
sbus36.rom	6.2	Turbo	WA-C301T, WA-C303T, WA-C306T, WA-C308T
sbus42.rom	7.3	Turbo	WA-C301T, WA-C303T, WA-C306T, WA-C308T

The appendix “Download Utilities” in the *Workgroup CDDI/FDDI SBus Adapter User Guide* describes how to use the download_flash utility to update the firmware on the SBus adapter.

The README file on the CDDI/FDDI SBus adapter driver for SunOS 4.1.x diskette contains detailed descriptions and configuration instructions for the following features:

- 2 Support for SMT revision 6.2 or 7.3.
- 3 Sunlink OSI 7.0.1 support (see the README file for the required Sun patch)
- 4 Sunlink DNI 7.0.1 support (see the README file for the required Sun patch)
- 5 IPT uShare Appletalk Version 4.0, Phase 2 support
- 6 Support for Helios EtherShare 2.2 AppleTalk package
- 7 Support for netatalk 1.3
- 8 Novell IPX support
- 9 Sunlink NetWare 1.0 IPX support

Cisco Information Online

Cisco Information Online (CIO) is Cisco Systems' primary, real-time support channel. Maintenance customers and partners can self-register on CIO to obtain additional content and services.

Available 24 hours a day, 7 days a week, CIO provides a wealth of standard and value-added services to Cisco's customers and business partners. CIO services include product information, software updates, release notes, technical tips, the Bug Navigator, configuration notes, brochures, descriptions of service offerings, and download access to public and authorized files.

CIO serves a wide variety of users through two interfaces that are updated and enhanced simultaneously—a character-based version and a multimedia version that resides on the World Wide Web (WWW). The character-based CIO (called "CIO Classic") supports Zmodem, Kermit, Xmodem, FTP, Internet e-mail, and fax download options, and is excellent for quick access to information over lower bandwidths. The WWW version of CIO provides richly formatted documents with photographs, figures, graphics, and video, as well as hyperlinks to related information.

You can access CIO in the following ways:

- WWW: <http://www.cisco.com>.
- Telnet: [cio.cisco.com](telnet://cio.cisco.com) (198.92.32.130).
- Modem: From North America, 408 526-8070; from Europe, 33 1 64 46 40 82. Use the following terminal settings: VT100 emulation; databits: 8; parity: none; stop bits: 1; and baud rates up to 14.4 kbps.

For a copy of CIO's Frequently Asked Questions (FAQ), contact cio-help@cisco.com. For additional information, contact cio-team@cisco.com.

Note If you are a network administrator and need personal technical assistance with a Cisco product that is under warranty or covered by a maintenance contract, contact Cisco's Technical Assistance Center (TAC) at 800 553-2447, 408 526-7209, or tac@cisco.com. To obtain general information about Cisco Systems, Cisco products, or upgrades, contact 800 553-6387, 408 526-7208, or cs-rep@cisco.com.

This document is to be used in conjunction with the publication *Workgroup CDDI/FDDI SBus adapter User Guide*.

Access Without Compromise, Catalyst, CD-PAC, CiscoFusion, Cisco Internetwork Operating System, Cisco IOS, CiscoView, CiscoWorks, HyperSwitch, LAN²LAN, LAN²LAN Enterprise, LAN²LAN Remote Office, LAN²PC, LightStream, Newport Systems Solutions, PC²LAN/X.25, Point and Click Internetworking, SMARTnet, SynchroniCD, *The Packet*, UniverCD, WNIC, Workgroup Director, Workgroup Stack, and XCI are trademarks; Access by Cisco and Bringing the power of internetworking to everyone are service marks; and Cisco, Cisco Systems, the Cisco logo, EtherSwitch, and Kalpana are registered trademarks of Cisco Systems, Inc. All other trademarks, service marks, registered trademarks, or registered service marks mentioned in this document are the property of their respective owners.

Copyright © 1995, Cisco Systems, Inc.
All rights reserved. Printed in USA
954R

